



BIG HULK SIGNAL BOOSTER ANTENNA

AvengeAngel Big Hulk signal booster antenna is a fantastic, active directional antenna with two 10W power amplifiers for a range extender, applicable to the 2.4GHz-2.5GHz and 5.0GHz-5.850GHz frequency band. It can enhance wireless signal strength, lengthen the transmission distance and stabilize signal reception, and it supports wifi and OcuSync Protocol.

APPLICABLE SCOPE

The AvengeAngel Big Hulk signal booster applies to all DJI Drones, and FPV drones and any drone that uses 2.4G and 5.8G band which include Mavic 3, Mavic 3 pro, Mavic 3E, Mavic 3T, Matrice 30, Matrice 300, Smart controller, Autel EVO/II/PRO.

Technical Specifications:

Working Frequency	2400-2500MHz 5000-5875MHz
Output Power	Two 10W amplifiers dual band output
Input Power	0~20dBm
Transmit Gain	20~22dB
Noise Figure	≤2.0dB
Transmission Delay	≤1μs
Antenna Gain	2.4G 15dBi±1 5.8G 18dBi±1
Supported Voltages	6-12V
Battery Voltage And Capacity	7.4V 5000mAh
Connector Type	N-K Female
LCD Screen Function	Battery level display

Mechanical Specifications

Antenna Signal Booster	250*155*54mm
Antenna Signal Booster Weight(g)	1680g
Operating Temperature	-35~+85°C
Operational Humidity(%)	Up to 75% relative humidity

Package contents

1 x Big Hulk Antenna Signal Booster
12V 2A Power adapter

