



AVENGEANGEL BIG HULK REPEATER

AvengeAngel Big Hulk Repeater is perfectly compatible with the AvengeAngel Big Hulk plus Antenna, designed and developed specifically for users with longer cable operation requirements. Through the signal transmission of the repeater, users can use longer cables to remotely control drones through the antenna.

AvengeAngel Big Hulk Repeater and AvengeAngel Big Hulk plus Antenna can reduce the signal loss of the cable transmission between the drone remote control and the antenna. 3 frequency bands 2.4~2.5GHz, 5.0-5.2GHz and 5.8GHz control channels are pre-enhanced signal strength, and the enhanced signal is transmitted to the antenna through the cable. The signal power of each frequency band is enhanced, ensuring that the drone's flight distance and anti-electronic interference capabilities are increased.

RECOMMENDED CABLE LENGTH COMBINATION

Remote control → Repeater 20-40M cable free choice

Repeater → Antenna 20-40M cable free choice

PRODUCT FEATURES

- After signal enhancement, signals can transmit through long cables (up to 40 meters);
- Works in 3 frequency ranges: 2.4, 5.2 and 5.8 GHz. works properly at any of 3 frequencies;
- Built-in long-time battery can work continuously for up to 10 hours. With an external power supply, it can work continuously 24/7;
- LCD battery level display, percentage shows battery level and charging status. turn off function suitable for concealed use at night;

■ Technical Specifications

Working Frequency	2400-2500MHz	5000-5875MHz
Supported Voltages	12V	
Battery Voltage and Capacity	7.4V 6400mAh	
Connector Type	N-K Female	
LCD Screen Function	Battery level display	

■ Mechanical Specifications

Big Hulk Repeater Size(mm)	250*155*54mm
Big Hulk Repeater Weight(g)	1680g
Operating Temperature	-35~+85°C
Operational Humidity(%)	Up to 75% relative humidity

■ Package contents

- 1 x Big Hulk Repeater
- 1 x 12V 3A Power Adapter



www.avengeangel.com